



FortiSwitch™-Compatible Transceivers

Transceiver specifications can be found in the [Fortinet Transceivers datasheet](#) on the Fortinet website.

Each row in the following table shows which FS-series, FG-series, and FR-series transceivers are compatible with each FortiSwitch model.

FortiSwitch Models	FS-TRAN-FX/FTLF1217P2BTL 100Mb	FG-TRAN-LX/AFCT-5710PZ 1G	FG-TRAN-GC/FCLF-8521-3 1G ³	FG-TRAN-SX/AFBR-5710PZ/ FTLF8519P3BNL 1G	FS-TRAN-GC/LCP-1250RJ3SR-K/ FCLF-8521-3 1G ³	FR-TRAN-ZX/FTLF1518P1BTL 1G	FR-TRAN-SX/FTLF8519P3BTL 1G	FG-TRAN-SFP+SR/AFBR-709ASMZ/ FTLX8571D3BCL/FTLX8574D3BCL 10G	FG-TRAN-SFP+LR/AFCT-739ASMZ/ FTLX1471D3BCL 10G	FS-TRAN-SFP+SR/FTLX8571D3BCV/ FTLX8574D3BCL 10G	FS-TRAN-SFP+ER/FTLX1672D3BCL 10G	FG-TRAN-QSFP+SR/FTL410QE2C/ QCP-10G3A4EDR 40G	FG-TRAN-QSFP+LR/FTL4C1QE1C 40G	FG-TRAN-QSFP+SR-BIDI/AFBR-79EBPZ 40G	FG-TRAN-QSFP28-SR4/ FTLC9551REPM 100G	FG-TRAN-QSFP28-LR4/ FTLC1151RDPL 100G
FS-108E	✓	✓	✓	✓	✓	✓	✓	—	—	—	—	—	—	—	—	—
FS-108E-POE	✓	✓	✓	✓	✓	✓	✓	—	—	—	—	—	—	—	—	—
FS-108E-FPOE	✓	✓	✓	✓	✓	✓	✓	—	—	—	—	—	—	—	—	—
FS-108F	✓	✓	✓	✓	✓	✓	✓	—	—	—	—	—	—	—	—	—
FS-108F-POE	✓	✓	✓	✓	✓	✓	✓	—	—	—	—	—	—	—	—	—
FS-108F-FPOE	✓	✓	✓	✓	✓	✓	✓	—	—	—	—	—	—	—	—	—
FS-110G-FPOE	—	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—	—	—	—	—
FS-124E	✓	✓	✓	✓	✓	✓	✓	—	—	—	—	—	—	—	—	—
FS-124E-POE	✓	✓	✓	✓	✓	✓	✓	—	—	—	—	—	—	—	—	—
FS-124E-FPOE	✓	✓	✓	✓	✓	✓	✓	—	—	—	—	—	—	—	—	—
FS-124F	—	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—	—	—	—	—
FS-124F-POE	—	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—	—	—	—	—
FS-124F-FPOE	—	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—	—	—	—	—
FS-124G	—	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—	—	—	—	—
FS-124G-FPOE	—	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—	—	—	—	—
FS-148E	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—	—	—	—	—
FS-148E-POE	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—	—	—	—	—
FS-148F	—	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—	—	—	—	—
FS-148F-POE	—	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—	—	—	—	—
FS-148F-FPOE	—	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—	—	—	—	—
FS-224D-FPOE	—	✓	✓	✓	✓	✓	✓	—	—	—	—	—	—	—	—	—
FS-248D	—	✓	✓	✓	✓	✓	✓	—	—	—	—	—	—	—	—	—
FS-224E	—	✓	✓	✓	✓	✓	✓	—	—	—	—	—	—	—	—	—
FS-224E-POE	—	✓	✓	✓	✓	✓	✓	—	—	—	—	—	—	—	—	—
FS-248E-POE	—	✓	✓	✓	✓	✓	✓	—	—	—	—	—	—	—	—	—
FS-248E-FPOE	—	✓	✓	✓	✓	✓	✓	—	—	—	—	—	—	—	—	—
FS-424D	—	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—	—	—	—	—
FS-424D-POE	—	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—	—	—	—	—
FS-424D-FPOE	—	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—	—	—	—	—
FS-424E	—	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—	—	—	—	—
FS-424E-POE	—	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—	—	—	—	—
FS-424E-FPOE	—	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—	—	—	—	—
FS-424E-Fiber ¹	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—	—	—	—	—
FS-M426E-FPOE	—	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—	—	—	—	—
FS-448D	—	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—	—	—	—	—
FS-448D-POE	—	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—	—	—	—	—
FS-448D-FPOE	—	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—	—	—	—	—
FS-448E	—	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—	—	—	—	—
FS-448E-POE	—	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—	—	—	—	—
FS-448E-FPOE	—	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—	—	—	—	—
FS-524D	—	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—	—	—	—	—
FS-524D-FPOE	—	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—	—
FS-548D	—	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—	—
FS-548D-FPOE	—	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—	—
FS-624F	—	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—	—	—	—	—

FortiSwitch Models	FS-TRAN-FX/FTLF1217P2BTL 100Mb	FG-TRAN-LX/AFCT-5710PZ 1G	FG-TRAN-GC/FCLF-8521-3 1G ³	FG-TRAN-SX/AFBR-5710PZ/ FTLF8519P3BNL 1G	FS-TRAN-GC/LCP-1250R3SR-K/ FCLF-8521-3 1G ³	FR-TRAN-ZX/FTLF1518P1BTL 1G	FR-TRAN-SX/FTLF8519P3BTL 1G	FG-TRAN-SFP+SR/AFBR-709ASMZ/ FTLX8571D3BCL/FTLX8574D3BCL 10G	FG-TRAN-SFP+LR/AFCT-739ASMZ/ FTLX1471D3BCL 10G	FS-TRAN-SFP+SR/FTLX8571D3BCV/ FTLX8574D3BCL 10G	FS-TRAN-SFP+ER/FTLX1672D3BCL 10G	FG-TRAN-QSFP+SR/FTL410QE2C/ QCP-10G3A4EDR 40G	FG-TRAN-QSFP+LR/FTL4C1QE1C 40G	FG-TRAN-QSFP+SR-BIDI/AFBR-79EBPZ 40G	FG-TRAN-QSFP28-SR4/ FTLC9551REPM 100G	FG-TRAN-QSFP28-LR4/ FTLC1151RDPL 100G
FS-624F-FPOE	—	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—	—	—	—	—
FS-648F	—	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—	—	—	—	—
FS-648F-FPOE	—	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—	—	—	—	—
FS-1024D	✓	✓	—	✓	✓	✓	✓	✓	✓	✓	✓	—	—	—	—	—
FS-1024E	—	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
FS-T1024E	—	—	—	—	—	—	—	—	—	—	—	✓	✓	✓	✓	✓
FS-T1024F-FPOE	—	—	—	—	—	—	—	—	—	—	—	✓	✓	✓	✓	✓
FS-1048D	✓	✓	—	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
FS-1048E	—	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
FS-1048G	—	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
FS-2048F	—	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
FS-3032D	—	—	—	—	—	—	—	—	—	—	—	✓	✓	✓	✓	✓
FS-3032E	—	—	—	—	—	—	—	—	—	—	—	✓	✓	✓	✓	✓
FS-3032G	—	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
FSR-108F	—	✓	✓	✓	✓	✓	✓	—	—	—	—	—	—	—	—	—
FSR-112D-POE	✓	✓	✓	✓	✓	✓	✓	—	—	—	—	—	—	—	—	—
FSR-112F-POE	—	✓	✓	✓	✓	✓	✓	—	—	—	—	—	—	—	—	—
FSR-124D	—	✓	✓	✓	✓	✓	✓	—	—	—	—	—	—	—	—	—
FSR-216F-POE	—	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—	—	—	—	—
FSR-424F-POE ²	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—	—

- For the FS-424E-Fiber model, the first 24 ports support 1G transceivers and FS-TRAN-FX (100Base-FX); ports 25-28 are 1G/10G capable.
- FSR-424F-POE supports FS-TRAN-FX using port13 to port24.
- The `set speed 1000auto` command is required when FG-TRAN-GC or FS-TRAN-GC is used with a FortiSwitch unit. For the FS-2048F model, supported on ports 57 and 58 only.

Each row in the following table shows which FN-series transceivers are compatible with each FortiSwitch model.

FortiSwitch Models	
	FN-TRAN-FX/FTL F1217P2BTLFTN 100Mb
	FN-TRAN-FE/WST-SFECIV-R6F 100Mb ⁵
	FN-TRAN-SFX/WST-S3CAIS-DP 100Mb ⁴
	FN-TRAN-GC/WST-SEACIV-R6F/LCP-1250RJ3SRTFN 1G ²
	FN-TRAN-SX/FTL F8519P3BNLFTN 1G
	FN-TRAN-SXI/FTL F8519P3BTLFTN 1G
	FN-TRAN-LX/WST-SFP-LX-IF/ FTL F1318P3BTLFTN 1G
	FN-TRAN-EX/WST-SFP-EX-IF 1G
	FN-TRAN-DSL/180-T 1G ¹
	FN-TRAN-SFP-1BD10/WST-SD4LDI1-D6F/SPBD-125FQAISFT1 1G
	FN-TRAN-SFP-1BU10/WST-SU3LDI1-D6F/ SPBD-128EQAISFT1 1G
	FN-TRAN-SFP-1BD40/WST-SD4LDI4-D6F/ SPBD-128FMAISFT1 1G
	FN-TRAN-SFP-1BU40/WST-SU3LDI4-D6F/ SPBD-128EMAISFT1 1G
	FN-TRAN-SFP2-SX/WST-SFP2-SX-IF 2.5G ³
	FN-TRAN-SFP2-LX/WST-SFP2-LX2-IF 2.5G ³
	FN-TRAN-SFP+SR/ LCP-10G3A4EDRZFN/FTL X8574D3BCLFTN 10G
	FN-TRAN-SFP+LR/WST-SFP+LR-IF/ FTL X1475D3BCLFTN 10G
	FN-TRAN-SFP+ER/FTL X1672D3BCLFTN 10G
	FN-TRAN-SFP+GC/WST-SFP+CuRMS-I// LCP-10GRJ3SRFN 10G
	FN-TRAN-SFP+ZR/FTL X1871D3BCLFTN 10G
	FN-TRAN-SFP+BD27 FTL X2672DN27FTN 10G
	FN-TRAN-SFP+BD33 FTL X2672DN33FTN 10G
	FN-TRAN-SFP+LRM/WST-SFP+LRM-C 10G
	FN-TRAN-SFP+GC-T80/WST-SFP+CuS-F 10G
	FN-TRAN-SFP+SRI/WST-SFP+SR-I 10G
	FN-TRAN-SFP+ERI/WST-SFP+ER-I 10G
	FN-TRAN-SFP+LRI/LCP-10GBQAI S-FT2/ WST-SFP+LR-IF 10G
	FN-TRAN-SFP28-SRWST-S28-SR-CF/ FTL F8536P4BCVFTN/FTL F8536P8BCVFTN 25G
	FN-TRAN-SFP28-LRWST-S28-LR-CF/ FTL F1436P3BCVFTN/FTL F1436W5BCVFTN 25G
	FN-TRAN-QSFP+SR/WST-QSFP+SR4-CF/ FTL410QE4CFTN 40G
	FN-TRAN-QSFP+LR/FTL4C1QE2CFTN 40G
	FN-TRAN-QSFP-BIDI/WST-QSFP+SRB-CF 40G
	FN-TRAN-QSFP+ER/FTL4E1QE1CFTN 40G
	FN-TRAN-QSFP+LR/WST-QSFP+LR4-I 40G
	FN-TRAN-QSFP28-SR/FTLC9558REPMFTN 100G
	FN-TRAN-QSFP28-LR/FTLC1154RDPLFTN 100G
	FN-TRAN-QSFP28-CWDM4/ FTLC1157RGPLFTN/FTLC1155RGPLFTN 100G
	FN-TRAN-QSFP28-ER/FTLC1156RDPLAF TN 100G
	FN-TRAN-QSFP28-DR/FTLC4352RHPLFTN/ FTLC4353RHPLFTN 100G
	FN-TRAN-QSFP28-FR/WST-QS28-FR-CF/FTLC4353RJPLFTN 100G
	FN-TRAN-QSFP28-BIDI/WST-QS28-SRB-C/AFBR -89BDDZ 100G
	FN-TRAN-QSFP28-BIDI-I/ OPCW-WX1-85-CBN 100G
FS-108E	<
FS-108E-POE	<
FS-108E-FPOE	<
FS-108F	<
FS-108F-POE	<
FS-108F-FPOE	<
FS-110G-FPOE	<
FS-124E	<
FS-124E-POE	<
FS-124E-FPOE	<
FS-124F	<
FS-124F-POE	<
FS-124F-FPOE	<
FS-124G	<
FS-124G-FPOE	<
FS-148E	<
FS-148E-POE	<
FS-148F	<
FS-148F-POE	<
FS-148F-FPOE	<
FS-224D-FPOE	<
FS-248D	<
FS-224E	<
FS-224E-POE	<
FS-248E-POE	<
FS-248E-FPOE	<
FS-424D	<
FS-424D-POE	<
FS-424D-FPOE	<
FS-424E	<
FS-424E-POE	<
FS-424E-FPOE	<
FS-424E-Fiber	<
FS-M426E-FPOE	<
FS-448D	<
FS-448D-POE	<
FS-448D-FPOE	<
FS-448E	<
FS-448E-POE	<
FS-448E-FPOE	<
FS-524D	<
FS-524D-FPOE	<
FS-548D	<
FS-548D-FPOE	<
FS-624F	<

CHANGE LOG	
July 11, 2018	Initial document release
July 12, 2018	Updated the 100G columns.
July 25, 2018	Added a table for direct-attach cables and split cables.
September 4, 2018	Changed the speed for FS-TRAN-FX. Added SP-CABLE cables.
May 16, 2019	Added rows for FS-3032E, FS-148E, and FS-148E-POE. Removed FortiSwitch models that do not support direct-attach cables and split cables from the second table.
June 13, 2019	Updated the FS-3032E row.
October 18, 2019	Added FN-TRAN-SFP+GC.
November 5, 2019	Added 3032E to the second table.
December 3, 2019	Corrected cable name.
December 10, 2019	Added FR-TRAN-ZX.
February 14, 2020	Removed FS-TRAN-SFP+GC and FS-TRAN-SFP+LRM. Added FS-424E, FS-424E-POE, FS-424E-FPOE, FS-424E-Fiber, and FS-M426E-FPOE.
March 12, 2020	Added FG-TRAN-QSFP+SR-BIDI/AFBR-79EBPZ. Updated which switches support FR-TRAN-ZX.
April 6, 2020	Added FS-448E, FS-448E-POE, and FS-448E-FPOE.
April 29, 2020	Added 1048E support for FG-TRAN-QSFP-4XSFP and FG-TRAN-QSFP-4SFP-5.
May 4, 2020	Added 13 FN-series transceivers. Corrected the FS-3032D row in the first table.
July 22, 2020	Added vendor part numbers to SP-CABLE cables.
August 17, 2020	Expanded the note for the FS-424E-Fiber model.
November 30, 2020	Removed SP-CABLE-FS-SFP+7/OPSFPP-T-07-PAB. Added the FS-1xxF models.
December 2, 2020	Removed FN-TRAN-GC support by the FS-1024D and FS-1048D models.
December 3, 2020	Removed FN-TRAN-GC and FCLF8521P2BTL.
January 15, 2021	Updated the FS-148F-FPOE row in the first table. Corrected the description of FR-TRAN-ZX.
March 22, 2021	Added FS-124F, FS-124F-POE, FS-124F-FPOE, FS-148F, FS-148F-POE, and FS-148F-FPOE to the Direct-Attach Cables and Split Cables table.
March 31, 2021	Updated note 2.
April 3, 2021	Added FS-1xxF support for FN-TRAN-SFP+LR, FN-TRAN-SFP+ER, and FG-TRAN-SFP+GC.
May 17, 2021	Updated note 1.
October 20, 2021	Added FN-TRAN-DSL.
November 30, 2021	Added FS-108F.
December 1, 2021	Updated the FS-TRAN-FX column (removed the 124F series and 148F series).
December 3, 2021	Added FN-TRAN-GC. Added FS-108F-POE, FS-108F-FPOE, FS-1024E, and FS-T1024E to the transceivers tables. Added support by FS-108E, FS-108E-POE, FS-108E-FPOE, FS-124E, FS-124E-POE, and FS-124E-FPOE for FS-TRAN-FX.
December 7, 2021	Added FS-1024E and FS-T1024E to the cables table.
December 15, 2021	Replaced FN-TRAN-GC (FCLF8522P2BTLFTN) with FN-TRAN-GC (LCP-1250RJ3SRTFN).
February 11, 2022	Updated the FS-T1024E row in each table. Removed FN-TRAN-SFP28-SR and FN-TRAN-SFP28-LR.
March 3, 2022	Added supported transceivers for the FS-124F, FS-124F-POE, FS-124F-FPOE, FS-148E, FS-148E-POE, FS-148F, FS-148F-POE, and FS-148F-FPOE models in the first table. Added supported transceivers for the FS-148E and FS-148E-POE models in the second table.
March 4, 2022	Updated the models supporting FG-TRAN-GC and FN-TRAN-DSL.
March 21, 2022	Corrected the models supporting FN-TRAN-GC (removed the support of FS-3032D and FS-3032E).

CHANGE LOG	
April 26, 2022	Removed the support of FS-1024E and FS-T1024E for FG-TRAN-QSFP-4SFP-5 and FG-TRAN-QSFP-4XSFP.
June 9, 2022	Added FR-TRAN-SX.
November 4, 2022	Added a second note (“The <code>set speed 1000auto</code> command is required when FN-TRAN-GC is used with a FortiSwitch unit.”) to the second table.
December 12, 2022	Added the following: - FN-CABLE-QSFP28-1/OPQS28-T-01-PEV - FN-CABLE-QSFP28-2/OPQS28-T-02-PEV - FN-CABLE-QSFP28-3/OPQS28-T-03-PEV - FN-CABLE-QSFP28-5/OPQS28-T-05-PEV - FN-CABLE-QSFP28-4SFP28-1/NDAQGF-FN01 - FN-CABLE-QSFP28-4SFP28-3/NDAQGJ-FN03 - FN-CABLE-QSFP28-4SFP28-5/NDAQGJ-FN05 - FN-TRAN-SFP+ZR - FN-TRAN-QSFP+ER - FN-TRAN-QSFP28-ER - FN-TRAN-QSFP28-DR Also added more manufacturing part numbers.
January 25, 2023	Removed the support of FS-124F, FS-124F-POE, and FS-124F-FPOE for SP-CABLE-FS-SFP+3/OPSFPP-T-03-PEB and SP-CABLE-FS-SFP+5/OPSFPP-T-05-PAB. Removed the support of FS-148F, FS-148F-POE, and FS-148F-FPOE for SP-CABLE-FS-SFP+5/OPSFPP-T-05-PAB.
March 17, 2023	Added FN-TRAN-SFP+BD27 and FN-TRAN-SFP+BD33.
June 19, 2023	Added FN-CABLE-SFP+1, FN-CABLE-SFP+3, and FN-CABLE-SFP+5.
June 20, 2023	Added the following: - FN-TRAN-QSFP28-BIDI-I/OPCW-WX1-85-CBN - FN-TRAN-QSFP28-BIDI/AFBR-89BDDZ - FN-CABLE-QSFP+1/NDAAEA-FN01 - FN-CABLE-QSFP+3/NDAAEA-FN03 - FN-CABLE-QSFP+5/NDAAED-FN05
June 23, 2023	Added FSR-424F-POE to the three tables.
August 1, 2023	Added the support of FS-1024E and FS-T1024E for FG-TRAN-QSFP-4XSFP and FG-TRAN-QSFP-4SFP-5.
October 13, 2023	Added FS-624F, FS-624F-FPOE, FS-648F, and FS-648F-FPOE to the three tables. Added FN-TRAN-SFP28-SR, FN-TRAN-SFP28-LR, FN-CABLE-SFP28-1, FN-CABLE-SFP28-3, and FN-CABLE-SFP28-5.
December 4, 2023	- Added FS-2048F to the three tables. - Added the support of FSR-424F-POE for FS-TRAN-FX. - Added note 2 to the first table. - Added the support of FS-1024E and FS-T1024E for FN-CABLE-QSFP28-4SFP28-1 and FN-CABLE-QSFP28-4SFP28-3. - Added FN-TRAN-SFP2-SX and FN-TRAN-SFP2-LX.
December 14, 2023	Added the FS-6xxF support for FG-TRAN-LX, FG-TRAN-GC, FG-TRAN-SX, FS-TRAN-GC, FR-TRAN-ZX, FR-TRAN-SX, FN-TRAN-GC, FN-TRAN-SX, FN-TRAN-LX, and FN-TRAN-DSL.
January 24, 2024	Removed the support of FN-TRAN-SFP2-SX and FN-TRAN-SFP2-LX for FS-T1024E.
February 6, 2024	Added FN-TRAN-SFP-1BD10, FN-TRAN-SFP-1BU10, FN-TRAN-SFP-1BD40, and FN-TRAN-SFP-1BU40.
March 4, 2024	- Added FN-TRAN-SFP+LRM and FN-TRAN-SFP+GC-T80. - Added note 3 for FN-TRAN-SFP2-SX and FN-TRAN-SFP2-LX.
April 9, 2024	Added the support of FS-108F, FS-108F-POE, FS-108F-FPOE, FSR-112D-POE, FS-2xxD, and FS-2xxE for FN-CABLE-SFP+1, FN-CABLE-SFP+3, and FN-CABLE-SFP+5; added note 2 to the third table.
July 26, 2024	Added FS-1024F-FPOE to the three tables.
July 29, 2024	Changed FS-1024F-FPOE to FS-T1024F-FPOE in all three tables.
August 15, 2024	Added FS-110G-FPOE to the three tables.
August 30, 2024	Removed the support of the FS-1xxF models for FN-CABLE-SFP+3.
October 17, 2024	Added the support of the FS-1xxF models for FN-CABLE-SFP+3.
November 6, 2024	Fixed the superscripts in the first table.
December 13, 2024	Added FN-TRAN-FX/FTLF1217P2BTLFTN, FTLF1436P3BCVFTN, FTLF8536P4BCVFTN, FTLF1436W5BCVFTN, and FTLF8536P5BCVFTN.
January 24, 2025	Added FSR-216F-POE to the three tables.

CHANGE LOG	
March 5, 2025	• Moved FN-TRAN-FX/FTLF1217P2BTLFTN from the first table to the second table. • Added additional part numbers to various cables and modules. • Added the following transceivers: ○ FN-TRAN-SFP+SRI/WST-SFP+SR-I ○ FN-TRAN-SFP+ERI/WST-SFP+ER-I ○ FN-TRAN-SFP+LRI/LCP-10GBQAIS-FT2/WST-SFP+LR-IF ○ FN-TRAN-QSFP+LRI/WST-QSFP+LR4-I
April 16, 2025	Added note 4 to the third table.
April 17, 2025	Added FS-124G and FS-124G-FPOE to the three tables.
April 18, 2025	Corrected note 4 for the third table.
June 25, 2025	Added LCP-10G3A4EDRZFN to FN-TRAN-SFP+SR.
July 1, 2025	Added FN-TRAN-SFX/WST-S3CAIS-DP and FSR-112F-POE.
July 2, 2025	Added FSR-108F. Removed support of FS-108F, FS-108F-POE, and FS-108F-FPOE for FN-TRAN-SFX.
August 6, 2025	Added FS-1048G to the three tables.
August 20, 2025	Updated note 1 of the third table.
November 5, 2025	• Added FS-3032G and FN-CABLE-QSFP+7/WST-QSFP+DACP4-7; updated note 2 of the second table; added note 3 to the first table. • Made the following corrections: ○ Changed OPQS28-T-01-PEV to OPQS28-T-01-PEVN. ○ Changed OPQS28-T-02-PEV to OPQS28-T-02-PEVN. ○ Changed OPQS28-T-03-PEV to OPQS28-T-03-PEVN. ○ Changed OPQS28-T-05-PEV to OPQS28-T-05-PBVN. • Added the support of FSR-112D-POE for FS-TRAN-FX and FN-TRAN-FX.
November 7, 2025	Added FTLC4353RHPLFTN to FN-TRAN-QSFP28-DR.
December 17, 2025	Added FN-TRAN-SXI/FTLF8519P3BTLFTN, FN-TRAN-FE/WST-SEFCIV-R6F, FN-TRAN-EX/WST-SFP-EX-IF, FN-TRAN-QSFP-BIDI/WST-QSFP+SRB-CF, and FN-TRAN-QSFP28-FR/WST-QS28-FR-CF/FTLC4353RJPLFTN to the second table.
December 18, 2025	Added the support of FS-448E, FS-448E-POE, FS-448E-FPOE, FSR-108F, FSR-112F-POE, FSR-216F-POE, and FSR-424F-POE for FN-TRAN-EX (second table).
February 27, 2026	Revised note 1 for table 3.

Copyright© 2026 Fortinet, Inc. All rights reserved. Fortinet®, FortiGate®, FortiCare® and FortiGuard®, and certain other marks are registered trademarks of Fortinet, Inc., in the U.S. and other jurisdictions, and other Fortinet names herein may also be registered and/or common law trademarks of Fortinet. All other product or company names may be trademarks of their respective owners. Performance and other metrics contained herein were attained in internal lab tests under ideal conditions, and actual performance and other results may vary. Network variables, different network environments and other conditions may affect performance results. Nothing herein represents any binding commitment by Fortinet, and Fortinet disclaims all warranties, whether express or implied, except to the extent Fortinet enters a binding written contract, signed by Fortinet’s General Counsel, with a purchaser that expressly warrants that the identified product will perform according to certain expressly-identified performance metrics and, in such event, only the specific performance metrics expressly identified in such binding written contract shall be binding on Fortinet. For absolute clarity, any such warranty will be limited to performance in the same ideal conditions as in Fortinet’s internal lab tests. In no event does Fortinet make any commitment related to future deliverables, features, or development, and circumstances may change such that any forward-looking statements herein are not accurate. Fortinet disclaims in full any covenants, representations, and guarantees pursuant hereto, whether express or implied. Fortinet reserves the right to change, modify, transfer, or otherwise revise this publication without notice, and the most current version of the publication shall be applicable.